FX-5 Interactive Showroom Screen Fixture

(46.75in wide x 72.25in high x 18.625in d)

Read all instructions before beginning any work.

Unit will not stand independently. Please KEEP UNIT ATTACHED TO PALLET until floor bolt holes are drilled and prepared for installation.

Electronics installation by third party shown separately.

Preparation:

Identify installation location per dealer location reference document.

Parts Included:

- Main fixture structure
- Back base enclosure and lid
- Floor drilling template
- Four floor anchor bolts & shims
 - •Four 1/4x20 bolts and washers

Tools & Materials Required:

- Corded hammer drill, 3/8" concrete drill bits at varied lengths based on floor situation.
- Hammer
- Small level
- Two floor roller dollies (one minimum)
- Box wrenches or socket set
- Cleaning supplies to wipe down unit. WITHOUT BLEACH or VINEGAR for use on laminate



FRONT

BACK

9



FX-5 Interactive Showroom Screen Fixture

Read all instructions before beginning any work.

Floor Bolting:

1) Determine location per dealer location reference document (consultation report) and confirm exact bolt location in this space with on-site Dealer point of contact.

2) Ask Dealer to use their pallet jack to get the fixture to the install location. If they do not have one, then use your 4 wheel dollies to move the pallet to its installation location. See instructional video on proper handling to get pallet onto 4-wheel dolly.

3) Remove banding from the fixture BUT DO NOT remove the remaining packaging until the unit is bolted and fully installed.

4) Remove the floor template and box containing hardware and back cover enclosure

5) Place the template in the mounting location (make sure the template is in the correct orientation for the front and back of the display)



FX-5 Interactive Showroom Screen Fixture *Read all instructions before beginning any work.*

6) Stand or kneel on the floor template and with hammer drill, drill first hole location through template.

7) Verify that holes drilled are at least 4" deep at minimum.

8) After drilling each hole, place the anchor bolt in the hole at least $\frac{1}{2}$ "-1" to keep the template from moving. Repeat this for the remaining 3 holes. Set template aside. It is no longer used.

9) Vacuum all dust from hammer drilling.

10) Using two people, remove the fixture from the pallet via four bolts. DO NOT let go of the fixture during the next 3 steps or remove remaining packaging until the unit is fully installed.

11) Using two people, LIFT the fixture onto the floor over the bolt holes.

- 12) Insert bolts and tap with hammer to get to full depth.
- 13) Secure bolts with washer and nuts using hex socket or box wrenches.

a. After each bolt is secured, check for level on front and side of display and using shims, adjust as needed.b. Repeat this for all 4 bolts making sure all are fully secured and unit is completely level.





FX-5 Interactive Showroom Screen Fixture *Read all instructions before beginning any work.*

14) After unit is confirmed to be 100% secured, remove remaining packaging.

15) Install the back cover enclosure and secure with four provided 1/4-20 bolts & wahsers.

16) Install top access lid onto backside enclosure box. Not bolted.

17) Clean up all packaging and area and dispose of in dealership dumpster.

18) Fill out DCI sign-off form completely and have on-site Dealer POC sign off on work completed

19) Take photos of completed unit from a distance to show fixture in context of the entire room and close-up photos of all sides.

